

**Magnetotelluric Data Release for Locating the
Archean/Proterozoic Suture Zone,
East-Central Tooele County, Utah**

By Jackie M. Williams and Brian D. Rodriguez

This report is preliminary and has not been reviewed for conformity with U.S. Geological Survey editorial standards and stratigraphic nomenclature.

Any use of trade, product, or firm names is for descriptive purposes only and does not imply endorsement by the U.S. Government.

U.S. Geological Survey Open-File Report 03-495

**U.S. DEPARTMENT OF THE INTERIOR
U.S. GEOLOGICAL SURVEY**

TABLE OF CONTENTS

INTRODUCTION	3
MAGNETOTELLURIC METHOD	3
MAGNETOTELLURIC SURVEY	4
MAGNETOTELLURIC DATA	5
REFERENCES CITED	8
APPENDIX - MAGNETOTELLURIC DATA PLOTS	10

INTRODUCTION

Many sediment-hosted gold deposits occur along linear trends in the Great Basin. The distribution and genesis of these deposits in the Great Basin is not fully understood. In general, most models agree that regional structures played an important role in the spatial distribution of these deposits (e.g. Arehart and others, 1993; Ilchik and Barton, 1997; Radtke, 1985; Shawe, 1991; Sillitoe and Bonham, 1990; Tosdal, 1998). To investigate crustal structures that may be related to the genesis of gold deposits in the Great Basin, a regional south-north profile of magnetotelluric (MT) soundings was acquired in 2003 (Figure 1). Resistivity modeling of the MT data can be used to investigate buried structures or sutures that may have influenced subsequent tectonism, sedimentation, and regional fluid flow. The goal of this survey is to infer the location of the Archean/Proterozoic suture zone in east-central Tooele County, Utah. The purpose of this report is to release the MT sounding data; no interpretation of the data is included.

MAGNETOTELLURIC METHOD

The magnetotelluric (MT) method is a passive surface geophysical technique, which uses the earth's natural electromagnetic fields to investigate the electrical resistivity structure of the subsurface. The resistivity of geologic units is largely dependent upon their fluid content, porosity, degree of fracturing, temperature, and conductive mineral content (Keller, 1989). Saline fluids within the pore spaces and fracture openings can reduce resistivities in a resistive rock matrix. Also, resistivity can be lowered by the presence of conductive clay minerals, carbon, and metallic mineralization. It is common for altered volcanic rocks to contain authigenic minerals that have resistivities ten times lower than those of the surrounding rocks (Nelson and Anderson, 1992). Increased temperatures cause higher ionic mobility and mineral activation energy, reducing rock resistivities significantly. Unaltered, unfractured igneous rocks are moderately to highly resistive (hundreds to thousands of ohm-m), whereas fault zones will show low resistivity (less than 100 ohm-m) when they are comprised of rocks fractured enough to have hosted fluid transport and consequent mineralogical alteration (Eberhart-Phillips and others, 1995). Carbonate rocks are moderately to highly resistive (hundreds to thousands of ohm-m) depending upon their fluid content, porosity, fracturing, and impurities. Marine shales, mudstones, and clay-rich alluvium are normally very conductive (a few ohm-m to tens of ohm-m). Unaltered, metamorphic rocks (non-graphitic) are moderately to highly resistive (hundreds to thousands of ohm-m). Tables of electrical resistivity for a variety of rocks, minerals and geological environments may be found in Keller (1987) and Palacky (1987).

The MT method can be used to probe the crust from depths of tens of meters to depths of tens of kilometers (Vozoff, 1991). Natural variations of the Earth's magnetic and electric fields are measured and recorded at each MT station. The primary frequency bands used by the MT method are 10,000 Hz to 1 Hz from worldwide lightning activity and 1 Hz to 0.0001 Hz from geomagnetic micro-pulsations. The natural electric and magnetic fields propagate vertically in the earth because the very large resistivity contrast between the air and the earth causes a vertical refraction of both fields transmitted into the earth (Vozoff, 1972).

The natural electric and magnetic fields are recorded in two orthogonal, horizontal directions. The vertical magnetic field ("tipper") is also recorded. The resulting time-series signals are used to derive the tensor apparent resistivities and phases. First, the signals are converted to complex cross-spectra using FFT (fast-Fourier-transform) techniques. Then, least-squares, cross-spectral analysis (Bendat and Piersol, 1971) is used to solve for a transfer function that relates the observed electric fields to the magnetic fields under the assumption that the Earth consists of a two-input, two-output, linear system with the magnetic fields as input and the electric fields as output. Prior to conversion to apparent resistivity and phase, the tensor is normally rotated into principal directions that correspond to the direction of maximum and minimum apparent resistivity. For a two-dimensional (2-D) Earth, the MT fields can be de-coupled into transverse electric (TE) and transverse magnetic (TM) modes; 2-D modeling is generally done to fit both modes. When the geology satisfies the 2-D assumption, the MT data for the TE mode is for the electric field parallel to geologic strike, and the data for the TM mode is for the electric field across strike. The MT method is well suited for studying complicated geological environments because the electric and magnetic relations are sensitive to vertical and horizontal variations in resistivity. The method is capable of establishing whether the electromagnetic fields are responding to subsurface terranes of effectively 1-, 2-, or 3-dimensions. An introduction to the MT method and references for a more advanced understanding are contained in Dobrin and Savit (1988) and Vozoff (1991).

MAGNETOTELLURIC SURVEY

Twelve stations were collected primarily along Skull Valley and extending south into the northern Sevier Desert in the summer of 2003. The station locations were chosen to cross the Archean/Proterozoic suture zone based on an inferred location from unpublished basement gravity maps (Grauch, 2003) and for proximity to roads and avoidance of electrical noise, such as power lines. All stations were collected with a portable EMI MT-1 system (EMI, 1996). Horizontal electric fields were sensed

using copper sulfate porous pots placed in an L-shaped, three-electrode array with dipole lengths of 30 m. The orthogonal, horizontal magnetic fields in the direction of the electric-field measurement array were sensed using permalloy-cored induction coils. Frequencies sampled ranged from 70 to .009Hz using single station recordings of both orthogonal horizontal components of the electric and magnetic fields, along with the vertical magnetic field.

The following table shows the twelve MT station locations as recorded using a global positioning system during field acquisition. Coordinates are referenced to the 1866 Clarke spheroid and North American 1927 Western United States datum. Longitude and latitude format is degrees:minutes:seconds. Universal Transverse Mercator units are in meters. Station elevation is given in meters. The accuracy of the x, y, and z component is + or - 5 meters.

<u>Station</u>	<u>Longitude</u>	<u>Latitude</u>	<u>UTM North(m)</u>	<u>UTM East (m)</u>	<u>Elev(m)</u>
12	-112:35:40	39:49:57	4,410,172	12,363,559	1530
11	-112:36:19	39:54:35	4,418,751	12,362,773	1665
10	-112:37:26	40:00:17	4,429,322	12,361,381	1830
9	-112:40:45	40:05:19	4,438,753	12,356,908	1560
8	-112:41:53	40:11:16	4,449,771	12,355,449	1495
7	-112:47:37	40:16:50	4,460,247	12,347,528	1540
6	-112:48:03	40:21:40	4,469,183	12,347,087	1415
5	-112:50:48	40:27:11	4,479,458	12,343,417	1360
4	-112:43:48	40:33:45	4,490,176	12,353,509	1390
3	-112:40:54	40:37:32	4,498,338	12,357,757	1380
2	-112:41:21	40:42:41	4,507,884	12,357,317	1295
1	-112:42:51	40:50:28	4,522,335	12,355,484	1300

MAGNETOTELLURIC DATA

The recorded time-series data were transformed to the frequency domain and processed to determine a two-dimensional apparent resistivity and phase tensor at each site. Rotation of the impedance tensor to maximum and minimum directions allows for decoupling into the TE and TM modes.

Although true remote reference techniques were not used in our survey, we did sort cross-power files to select optimal signal-to-noise time series data sets (see Appendix).

The effects of near-surface resistivity anomalies cause "static shifts" (Sternberg et al., 1988) in the data. Static shift is significant in stations 2, 4, 7, and 8. Cultural features can affect the response of the MT system. Fences, pipelines, communication lines, railways and other man-made conductors can contaminate the responses.

The figures in the Appendix represent the field-processed MT data for each station after the time series data were converted to the frequency domain and the tensor-transfer function was

rotated into principal directions as described above in the "Magnetotelluric Method" section.

For each station, nine separate plots are given:

1. Apparent Resistivity
2. Impedance Phase
3. Rotation Angle
4. Impedance Skew
5. Multiple Coherency
6. Impedance Polar Plots
7. Tipper Magnitude
8. Tipper Strike
9. HzHx and HzHy Coherency

Error bars on the Apparent Resistivity, Impedance Phase, Skew, Tipper Magnitude, and Tipper Strike plots represent probable errors within one standard deviation of the sample variance (Gamble and others, 1979).

Apparent resistivity is the ratio of the electric field strength magnitude over the magnetic field strength magnitude for a given frequency. The impedance phase is proportional to the slope of the apparent resistivity curve on a log-log plot, but from a baseline at -45 degrees (Vozoff, 1991). A measure of the dimensionality for MT data is provided by the impedance skew of the impedance tensor (Vozoff, 1972). If the effective measured resistivity response to the geology beneath a MT station is truly 1-D or 2-D, then the skew will be zero. Both instrument and environmental sources of noise contribute to non-zero skew values, but are typically small (about 0.1) for relatively low noise level recordings. Higher skews (above 0.2) are an indication of either the resistivity response to 3-D geology or higher levels of noise. Man-made electrical noise, such as power lines, power generators, moving vehicles and trains can have a negative effect on MT data quality. All of these local disturbances produce an incoherent noise mainly affecting frequencies above 1 Hz. Other man-made electrical noise, such as direct current electric trains and active cathodic protection of pipelines produce coherent electromagnetic signals mainly affecting frequencies below 1 Hz.

In the survey area, noise from a number of small power lines and small moving vehicles was negligible at distances of 0.4 km and greater from the noise source. Power line levels were measured at each site and were typically less than 20% of the maximum recordable signals. Noise from larger power lines, power generators, pipelines, and trains was negligible at distances greater than 5 km from those noise sources. Local lightning, wind, and rainstorms can also degrade data quality. These were avoided by not recording during active thunderstorm periods, burying the magnetic induction coils and keeping the electric dipole wires flat on the ground surface minimizing wind noise.

Predicted values of the electric field can be computed from the measured values of the magnetic field (Vozoff, 1991). The coherence of the predicted electric field with the measured electric field is a measure of the signal-to-noise ratio provided in the multiple coherency plots. Values are normalized between 0 and 1, where values at 0.5 signify signal levels equal to noise levels. For this data set, coherencies were generally at an acceptable level, except at times in the frequency range "dead band" (.1 to 5 Hz).

The figures in the Appendix represent the field-processed MT data at each station, which includes some data scatter and poor signal-to-noise ratios. Our only effort at removing noisy data points was to visually inspect and select the best signal-to-noise field data to combine into the final data plots.

The impedance polar plots provide a measure of the MT data dimensionality (Reddy and others, 1977). For 1-D resistivity structures, the principal impedance polar diagram (dashed line) is a circle. For 2-D or 3-D resistivity structures, the principal impedance polar diagram (dashed line) elongates either parallel or perpendicular to strike direction. Over resistors, the principal impedance polar diagram elongates perpendicular to strike direction and over conductors, the principal impedance polar diagram elongates parallel to strike direction. Also, for 2-D resistivity structures, the additional impedance polar diagram (solid line) attains the shape of a symmetric clover leaf. For 3-D resistivity structures, the additional impedance polar diagram (solid line) elongates in one direction and its amplitude is comparable to that of the principal impedance polar diagram (dashed line). Stations 8 and 9 indicate a 3-D response below 0.05 Hz and 0.4 Hz, respectively.

The tipper can be calculated when the vertical component of the magnetic field is measured. The tipper magnitude is a measure of the tipping of the magnetic field out of the horizontal plane (Vozoff, 1991). The magnitude is zero for the 1-D case and typically increases between 0.1 to 0.5, and rarely as great as 1, as it responds to vertical and sub-vertical structures. The tipper strike is typically used to help resolve the 90-degree ambiguity in the impedance rotation angle. The tipper magnitude of these stations was typically 0.1 to 0.6 over the lower frequencies indicating some vertical structure at depth. The HzHx and HzHy coherency is a measure of the signal-to-noise ratio of the vertical magnetic field with respect to each of the orthogonal horizontal magnetic field directions. Values are normalized between 0 and 1, where values at 0.5 signify signal levels equal to noise levels. These three-component magnetic field coherencies provide a check on the signal-to-noise ratio of the measured values in the tipper magnitude and tipper strike plots.

REFERENCES CITED

- Arehart, G.B., Foland, K.A., Naeser, C.W., and Kesler, S.E., 1993, $^{40}\text{Ar}/^{39}\text{Ar}$, K/Ar, and fission track geochronology of sediment-hosted disseminated gold deposits at Post-Betze, Carlin Trend, northeastern Nevada: *Economic Geology*, vol. 88, no. 3, p. 622-646.
- Bendat, J.S., and Piersol, A.G., 1971, *Random Data: Analysis and Measurement Procedures*: New York, Wiley Interscience, 407p.
- Dobrin, M.D., and Savit, C.H., 1988, *Introduction to Geophysical Prospecting* (4th ed.): New York, McGraw-Hill, 867p.
- Eberhart-Phillips, D., Stanley, W.D., Rodriguez, B.D. and Lutter, W.J., 1995, Surface seismic and electrical methods to detect fluids related to faulting: *Journal of Geophysical Research*, vol. 100, no. B7, p. 12,919-12,936.
- EMI, 1996, MT-1 magnetotelluric system operation manual, version 3.2: ElectroMagnetic Instruments, Inc., Richmond, California, 220 p.
- Gamble, T.D., Goubau, W.M. and Clarke, J., 1979b, Error analysis for remote reference magnetotellurics: *Geophysics*, v. 44, no. 5, p. 959-968.
- Grauch, V.J.S., 2003, Personal communications: U.S. Geological Survey, Denver, Colorado.
- Ilchik, R.P. and Barton, M.D., 1997, An amagmatic origin of Carlin-type gold deposits: *Economic Geology*, vol. 92, no. 3, p. 269-288.
- Keller, G.V., 1987, Rock and mineral properties, in *Electromagnetic Methods in Applied Geophysics Theory*: M.N. Nabighian, Ed., Society of Exploration Geophysicists, Tulsa, Oklahoma, v. 1, p. 13 51.
- Keller, G.V., 1989, Electrical properties, in Carmichael, R.S., Ed., *Practical handbook of physical properties of rocks and minerals*: CRC Press, Boca Raton, Florida, p. 359-427.
- Nelson, P.H. and Anderson, L.A., 1992, Physical properties of ash flow tuff from Yucca Mountain, Nevada: *Journal of Geophysical Research*, vol. 97, no. B5, p. 6823-6841.

- Palacky, G.J., 1987, Resistivity characteristics of geologic targets, in *Electromagnetic Methods in Applied Geophysics Theory*: M.N. Nabighian, Ed., Society of Exploration Geophysicists, Tulsa, Oklahoma, vol. 1, p. 53-129.
- Radtke, A.S., 1985, Geology of the Carlin gold deposit, Nevada: U.S. Geological Survey Professional Paper 1267, 124 p.
- Reddy, I.K., Rankin, D., and Phillips, R.J., 1977, Three-dimensional modelling in magnetotelluric and magnetic variational sounding: *Geophysics Journal of the Royal Astronomical Society*, vol. 51, p. 313-325.
- Shawe, D.R., 1991, Structurally controlled gold trends imply large gold resources in Nevada, in *Geology and ore deposits of the Great Basin, Symposium Proceedings*: Raines, G.L., Lisle, R.E., Schafer, R.W., Wilkinson, W.H., Eds., Geological Society of Nevada, Reno, vol. 1, p. 199-212.
- Sillitoe, R.H. and Bonham, H.F., 1990, Sediment-hosted gold deposits; distal products of magmatic-hydrothermal systems: *Geology*, vol. 18, no. 2, p. 157-161.
- Sternberg, B.K., Washburne, J.C., and Pellerin, L., 1988, Correction for the static shift in magnetotellurics using transient electromagnetic soundings: *Geophysics*, vol. 53, p. 1459-1468.
- Tosdal, R.M., 1998, Contributions to the gold metallogeny of northern Nevada: U.S. Geological Survey Open-File Report 98-338, 290 p.
- Vozoff, K., 1972, The magnetotelluric method in the exploration of sedimentary basins: *Geophysics*, vol. 37, p. 98-141.
- Vozoff, K., 1991, The magnetotelluric method, in *Electromagnetic methods in applied geophysics*: M.N. Nabighian, Ed., Society of Exploration Geophysicists, Tulsa, Oklahoma, vol. 2, part B, p. 641-711.

APPENDIX
MAGNETOTELLURIC DATA PLOTS

There are nine separate plots for each station:

1. Apparent Resistivity for the rotated maximum (x symbol) and minimum (o symbol) modes
2. Impedance Phase for the rotated maximum (x symbol) and minimum (o symbol) modes
3. Rotation Angle for the impedance tensor (corresponds to the direction of maximum apparent resistivity)
4. Impedance Skew for the impedance tensor
5. Multiple Coherency for the rotated maximum (x symbol) and minimum (o symbol) modes of the electric field
6. Impedance Polar Plots (at 12 selected frequencies)
7. Tipper Magnitude for the vertical magnetic field
8. Tipper Strike for the vertical magnetic field
9. HzHx (x symbol) and HzHy (o symbol) Coherency

Refer to the "Magnetotelluric Data" section in this report for an explanation of these plots.